

GVN VRK

VRK-M3 SERIE

THREE PHASE VARIAC TESTER
3 – 15kVA

It allows to set the desired voltage automatically by manual or servo motor in the setting range determined according to customer request.

The variac, which is contained therein, is formed by winding a single envelope enamelled copper wire on toroidal sheet.

The variac provides all the load that provides power and voltage regulation. Using the MSC-7203 multimeter mounted on the variac box, the input voltage, the output voltage and the drawn amperage can be seen instantaneously. In addition, the MSC-7203 multimeter automatically records the highest and lowest values of the instantaneous values and can reset it as desired.



Ürün Kodu	Güç KVA	380 V	430V	A	B	H	KG
		Sekonder Amper	Sekonder Amper				
GVN-VRKM3	3x0.5	3x2,2	3x2	25	35	75	23
GVN-VRKM3	3x1.0	3x4,5	3x4	25	35	75	34
GVN-VRKM3	3x1.5	3x6,8	3x6	25	35	75	44
GVN-VRKM3	3x2.0	3x9,0	3x8	25	35	75	47
GVN-VRKM3	3x2.5	3x11,3	3x10	25	35	75	56
GVN-VRKM3	3x3.5	3x15,9	3x14	25	35	75	68
GVN-VRKM3	3x4.5	3x20,4	3x18	25	35	75	81
GVN-VRKM3	3x5.0	3x22,7	3x20	25	35	75	82

Recording the highest and lowest values seen

Resetting information

Input-output voltage and ampere calibration

Wide voltage range

Terminal or socket outlet

Circuit breaker for protection

High efficiency silent operation

Manual or automatic adjustment

Quality, ergonomic structure, easy carrying apparatus

Production in ISO 9001: 2008 and CE Standards.